

# US 50 Installation Guide

## Hand-free Stand



### Overview

Thank you for purchasing Cino US50 Hand-free Stand. The US50 is designed for hand-free applications, delivering great flexibility to maximize users' comfort and productivity. It's suitable for all Cino 1D and 2D handheld scanners. This document provides an easy reference for assembling and installing the US50.



#### Assemble the Stand



- Insert the small end of the tube into the hole on the top of the stand base.
- Place the small spacer on the screw hole on the bottom of the base plate and stand base, and insert an S1 flat head screw into the screw hole, then tighten the screw to secure the tube to the stand base.
- Paste the black patch on the bottom to cover the screw hole.
- Fit the scanner holder into the big end of the tube properly.
- Place the big spacer on the screw hole of the holder and insert an S1 screw into the screw hole, then tighten the screw to secure the holder to the tube.

The stand is now ready to be used with the scanner.



The stand is specially designed to work with all FuzzyScan family, including corded and cordless handheld scanners.

Put your FuzzyScan scanner onto the stand, then bend the tube to the desired position for the most optimized scanning.

Presentation mode allows you to scan bar code without holding your scanner in hand. In presentation mode, the scanner will automatically detect and scan bar code. The bar code may not be detected by the scanner in dim ambient light environment. You can set higher sensitivity level on your scanner to increase its detection sensitivity. Please visit CINO website for more details.

#### Mount the Stand



You can attach the stand to a flat surface by using two S2 screws. Please follow the steps below.

- Position the assembled base on a flat surface.
- Insert the two S2 screws into the screw-mount holes, then tighten the screws until the stand is secure.



US50 Installation Guide International Edition, Rev. A1



P/N: YMAUF00020010R0

#### **CINO GROUP** PC WORTH INT'L CO., LTD.

© Copyright PC Worth Int'l Co., Ltd. © Copyright Cino Group

